

NTZA-1200

أمبليفاير بقوة 120 وات (قناتين)

Power Amplifier 120W (2 Channels)



TECHNICAL SPECIFICATIONS

البيانات الفنية

Model	NTZA-1200
Features	Echo For Each Channel
Rated Power 120 Watts divided into 2 channels	Zone – A Zone – B 60 W 60 W
Inputs	5 X MIC 0.60mv/4.7kΩ 2 X AUX 100mv/470Ω AUX Input can be changed to mic via the switch
Line Voltage	4-8-16 Ω / 100 V Line
Freq. Response	65HZ -15KHz
Tone Control	BASS = 10dB AT 100Hz. TREBLE = 10dB AT 10kHz.
Pre-Amp. Output	200mV/600 Ohms
Power Supply	AC: 220-240V, 50/60 Hz. DC: 12VDC : 12V DC. 5A Battery
Packing Unit	Unit Weight: 9.5 Kg - Cartoon Weight: 11 Kg Unit Dim. : 430x260x145 mm Box Dim. : 500x310x190 mm Packing: 1 Piece - Cartoon: 2 Units

موديل	NTZA-1200
المميزات	صدي لكل قناة بشكل مستقل
قوة الصوت 120 وات	قناة A قناة B 60 وات 60 وات
مقسم على قناتين	
مداخل الصوت	5 x ميكروفون 0.65 م.ف / 4.7 ك. اوم 2 x مساعد 100 م.ف / 470 اوم مدخل المساعد يمكن تعديله الى مايك من خلال مفتاح التحويل
نظام التشغيل (مخرج الصوت)	4 - 8 - 16 اوم / 100 فولت
استجابة التردد	65 هرتز - 15 ك هرتز
تحكم وزنية الصوت	تضخيم BASS 10 ديسبل عند 100 هرتز طبقة صوت العالي TREBLE 10 ديسبل عند 10 ك. هرتز
مخرج إشارة الصوت	200 م. فول ت / 600 اوم
التغذية الكهربائية	تيار متردد: 220 - 240 ف، 50 / 60 هرتز تيار مستمر: 12 فولت
وحدة التعبئة	وزن الوحدة: 9.5 كغ - وزن الكرتون: 11 كغ أبعاد الوحدة: 430x260x145 مم أبعاد الكرتون: 500x310x190 مم التعبئة: 1 وحدة - الكرتون: 2 وحدة



More info at:

nedaksa.com

